



This easy add on emergency flasher switch is a simple heavy duty switch which requires a 1/2" mounting hole. The switch also requires a separate flasher that is fused to protect the circuit.

**Blue:** Splice to the right front turn signal wire.  
**White:** Splice to the right rear turn signal wire.  
**Yellow:** Splice to the left rear turn signal wire.  
**Green:** Splice to the left front turn signal wire.  
**Pink:** Connect to the emergency flasher. The flasher should be connected to a "fused" battery feed circuit.

**RON FRANCIS**  
*Wiring*

**FW-54**

**SYNERGY  
 SERIES**

**TOGGLE  
 EMERGENCY  
 FLASHER SWITCH**

Four-Way Hazard Switch  
 with matching Bezel & Accent Rings