

RON FRANCIS
Wiring

GP-9
Gear Shift Indicator
Lights & Plate
(Vertical/Silver)

Mount the shift indicator in the dash board as desired **OR** until aligned, you may wish to keep the indicator lights in sight from under the car to speed setup. Park and neutral use a yellow light, Reverse uses a red light, "D" uses the blue light and the rest of the forward gears use green lights.

12 volt ignition must be supplied to the red wire in the gray cable. Connect the red wires from each indicator light in the following order:

P ● Green
R ● White
N ● Black
D ● Orange
2 ● Blue
1 ● Brown

The Park light is wired to the Lt. Green wire, Reverse is White, Neutral is Black, Drive is Orange, Second is Lt. Blue and Low is wired to the Brown wire. Ground for the indicator lights is done by tying all the yellow wires together and running them to ground.

© 1997 Ron Francis'

P:\INST\GP-9